



14-Slot Media Converter Chassis

Includes redundant power supply, 19" rackmountable, 2U

Part No.: **507356**

EAN-13: 0766623507356 | UPC: 766623507356

The Intellinet Network Solutions 507356 Media Converter Chassis accommodates up to 14 media converters in a single unit

Reliability and Functionality

The 507356 Media Converter Chassis allows hot-swapping the media converters, and provides strong redundancy due to its two integrated power supplies. Two high-volume cooling fans ensure a cool operating environment.

Features:

- High-quality 19" rackmount steel chassis
- Supports up to 14 stand-alone media converters
- Two internal 100 – 260V universal switching power supplies avoid network downtime and protect your converter investments
- Power supplies support load sharing, and circuit-breakers protect against over voltage and short circuits
- Two high-volume cooling fans ensure perfect ventilation
- Slot power isolation ensures each slot is electrically isolated from the next
- Three-Year Warranty

Specifications:

- Capacity: 14 slots for up to 14 media converters
- Occupies 2 height units (2U)
- Certifications: FCC Class A, CE

Compatibility

- Fast Ethernet Media Converter 506502
- Fast Ethernet Media Converter 506519
- Fast Ethernet Media Converter 507332
- WDM Fast Ethernet Media Converter 510530
- WDM Fast Ethernet Media Converter 510547
- Gigabit Ethernet Media Converter 506533
- Gigabit Ethernet Media Converter 507349
- Gigabit Ethernet Media Converter 510493
- WDM Gigabit Ethernet Media Converter 545068
- WDM Gigabit Ethernet Media Converter 545075

LEDs

- LED for each power supply

Power

- Input: 100 – 260 VAC
- Output: 5 VDC

Environmental

- Material: aluminum/steel
- Dimensions: 482 (L) x 231 (W) x 90 (H) mm / 19 (L) x 9.09 (W) x 3.54 (H) in.
- Weight: 4.7 kg (10.3 lbs.)
- Operating temperature: 0 – 50°C (32 – 122°F)
- Operating humidity: 5 – 95% RH, non-condensing
- Storage temperature: -20 – 85°C (-4 – 185°F)

Package Contents

- Media Converter Chassis with 2 integrated power supplies
- 14 media converter carrier brackets
- Installation instructions



